



## WR-102 Standard Gain Horn Antenna Operates From 7 GHz to 11 GHz With a Nominal 15 dB Gain WR-102 Input

## **TECHNICAL DATA SHEET**

PE9857-15

WR-102 Standard Gain Horn Antenna Operates From 7 GHz to 11 GHz With a Nominal 15 dB Gain WR-102 Input

Configuration

Design WR-102 Standard Gain Horn

Frequency Range, GHz 7 to 11
Polarization Linear
Interface 1 WR-102

**Electrical Specifications** 

Nominal Gain, dB 15

**Mechanical Specifications** 

Size

 Length, in [mm]
 6.15 [156.21]

 Width, in [mm]
 3.145 [79.88]

 Height, in [mm]
 2.355 [59.82]

Compliance Certifications (visit www.Pasternack.com for current document)

**Plotted and Other Data** 

2 Dimensional OML Drawing PE9857-15

Notes: Values at 25 °C, sea level

WR-102 Standard Gain Horn Antenna Operates From 7 GHz to 11 GHz With a Nominal 15 dB Gain WR-102 Input from Pasternack Enterprises has same day shipment for domestic and International orders. Our RF, microwave and fiber optic products maintain a 99% availability and are part of the broadest selection in the industry.

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: WR-102 Standard Gain Horn Antenna Operates From 7 GHz to 11 GHz With a Nominal 15 dB Gain WR-102 Input PE9857-15

URL: http://www.pasternack.com/standard-gain-horn-waveguide-size-wr102-pe9857-15-p.aspx

The information contained in this document is accurate to the best of our knowledge and representative of the part described herein. It may be necessary to make modifications to the part and/or the documentation of the part, in order to implement improvements. Pasternack reserves the right to make such changes as required. Unless otherwise stated, all specifications are nominal.

Pasternack Enterprises, Inc. • P.O. Box 16759, Irvine, CA 92623

Phone: (866) 727-8376 or (949) 261-1920 • Fax: (949) 261-7451

Sales@Pasternack.com • Techsupport@Pasternack.com

## PE9857-15 CAD Drawing

WR-102 Standard Gain Horn Antenna Operates From 7 GHz to 11 GHz With a Nominal 15 dB Gain WR-102 Input

